

# HIGHER LOADS & INCREASED SAFETY

Redco™ SHEAVES

There are numerous advantages of a Redco<sup>™™</sup> Sheave over conventional steel or iron sheaves. These advantages include:

- EIGHT WEIGHT

  Redco™ Sheaves are 1/8th the weight of steel or iron sheaves. This improves the lifting capabilities of mobile and fixed boom cranes and eases installation.
- LONGER ROPE LIFE

  Redco™ Cast Sheaves are better suited to the "on again, off again" loading typical for this application. With enhanced material memory and resiliency, the rope grooves will flex under the load of the rope providing increased support to the rope.
- INCREASED LOADS

  The arm weight of telescoping cranes is decreased because Redco™ Sheaves are lighter. Also, Redco™ Sheaves flex under the load of the rope increasing the contact area between the rope and groove which increases load capacity.
- DECREASED OPERATING COSTS
  With lubricated grades of Redco™ Cast Nylon, the need for regular lubrication can be reduced or omitted.
- ORROSION RESISTANT
  Redco™ Cast Nylon Sheaves will not rust or corrode.


## SHEAVE DIAMETER

The outer diameter of the sheave depends on the size of the rope and load. The guideline for the sheave diameter is given by the Power Crane & Shovel Associations and American National Standards Institute. That guideline is given as a ratio between the "Pitch Diameter" of the shave and the "Rope Diameter". The minimum recommended ratio is 18:1. European standards require 24:1.

The following table will assist in determining the Pitch Diameter and outer diameter of the sheave.

Rope Dia	PD Ratio 18:1	OD	PD Ratio 24:1	OD
1/4	4 1/2	5 1/8	6	6 5/8
3/8	6 3/4	7 11/16	9	9 15/16
1/2	9	10 1/4	12	13 1/4
5/8	11 1/4	12 13/16	15	16 9/16
3/4	13 1/2	15 3/8	18	19 7/8
7/8	15 3/4	17 15/16	21	23 3/16
1	18	20 1/2	24	26 1/2
1 1/4	22 1/2	25 5/8	30	33 1/8
1 1/2	27	30 3/4	36	39 3/4

The Outer Diameter is based on a recommended groove depth that is 1.75 times the rope diameter.



## **Groove Design**

The groove depth should be at least 1.75 times the rope diameter.


The radius at the bottom of the groove should be slightly larger than the rope;

$$G = 1.05 * r/2$$

G = Groove radius

r = rope diameter

Typically, the groove angle is  $30^\circ$ . This provides for better rope support. On occasion, a  $45^\circ$  angle is required for increased fleet angles (up to  $4^\circ$ ).



#### **Rim Dimensions**

It is recommended to have a minimum shoulder width (distance between the outer edge of the rim and inside the groove) of 1/8". This allows for sufficient side loading support. With this, a calculation can be done to determine the width of the sheave at the rim.

Below is a table to determine the rim width based on the rope diameter, 30° groove angle, and 1/8" shoulder.

The minimum thickness of the sheave at the rim can be expressed as a function of the rope diameter (r).

$$T = \frac{1}{4} + 2.99r$$

$$\frac{30^{\circ}}{\frac{1}{4} + 2.99r}$$

$$\frac{35^{\circ}}{\frac{1}{4} + 3.18r}$$

$$\frac{40^{\circ}}{\frac{1}{4} + 3.38r}$$

$$\frac{45^{\circ}}{\frac{1}{4} + 3.59r}$$

T = Thickness at the rim

r = rope diameter

This is useful for calculating the Length-through-bore (LTB) on a straight walled, machined Redco™ Sheave.

#### Web for Redco™ Sheave


To further reduce the weight of a Redco $^{\text{m}}$  Sheave, material can be removed between the rim and the hub. Reducing the weight can ease installation as well as increase the carrying capacity of a boom style crane.

The minimum thickness of the web area is calculated as:

W = Web thickness

r = rope diameter

The transition between the web and the rim should either be a radius or a slope to avoid sharp angles.



#### **Bore Dimension**

To increase the load bearing capacity of a Redco<sup>™</sup> Sheave a metallic bushing or roller bearing can be used. The roller bearing allows for increased PV (pressure velocity) as well as the ability to carry increased loads. Special attention must be given to the press fit of the bearing or bushing into the sheave. A press fit that is too small will cause the sheave to walk off the bearing at increased temperatures.

The recommended amount of press fit can be calculated as:

$$p = .009 \sqrt{Db}$$

p = press fit Db = Diameter of the bearing or bushing

- The diameter of the bore must be machined to the size of the bearing/bushing less the calculated press fit. On larger sheaves, a hydraulic press is required to install the bearing.
- It is not recommended to heat up the sheave above 200°F as this can impart stress in the Redco™ Sheave.
- For thin walled bushings or bearings, a reduction in the press fit can be made. To avoid "walk-off" problems, the temperature swing should be kept to a minimum.
- For added bearing stability, retaining rings can be used. Also, thrust washers or collars can be attached to the shaft to keep the sheave from sliding from side to side.

#### **Hub Width**

The hub width is usually determined by the space available for the sheave, loading and stability requirements. The hub is typically as wide or wider than the rim.

The outer diameter of the hub is calculated by:

H = 1.5B

H = Hub diameter B = Bore diameter

• The minimum wall thickness of the hub is 1".

 The transition between the hub and web should either be a radius or a slope to avoid sharp angles.



## Load Capacity for Redco™ Sheaves: with Bearings

The GROOVE AND BORE PRESSURE can be calculated by:

For rope wrap angle of 180° For rope wrap angle of 90°


 $Pg = 2 \cdot T/r \cdot Dt$   $Pg = 1.414 \cdot T/r \cdot Dt$ 

 $Pb = 2 \cdot T/B \cdot LTB$   $Pb = 1.414 \cdot T/B \cdot LTB$ 

 $\begin{array}{lll} \text{Pg} = & \text{Groove Pressure (psi)} & \text{T} = & \text{Line Pull (lbs)} \\ \text{r} = & \text{rope diameter (in.)} & \text{Dt} = & \text{Tread Diameter (in.)} \end{array}$ 

Pb = Bore Pressure (psi) B = Bore Diameter LTB = Length through bore

Please refer to Fig. 1 on Page. 3



90° Wrap Angle

Fig. 4

To calculate the MAXIMUM BORE AND GROOVE PRESSURE acting on the sheave, substitute the maximum line pull for the rope to be used into the above equations.

The maximum static pressure for a Redco<sup>™</sup> Sheave is 4,000 psi. Intermittently, Redco<sup>™</sup> Sheaves can withstand up to 8,000 psi (for a few minutes). Using 4,000 psi as the maximum pressures, the above equations can be used to calculate the maximum line pull (Tmax).

For rope wrap angle of 180° For rope wrap angle of 90°

Groove  $Tmax = 2000 \cdot r \cdot Dt$   $Tmax = 2828 \cdot r \cdot Dt$ 

Bore  $Tmax = 2000 \cdot B \cdot LTB$   $Tmax = 2828 \cdot B \cdot LTB$ 

Note:

For a sheave ratio greater than 18:1, calculate only bore pressure.

## Load Capacity for Redco™ Sheaves:

without Bearings (Redco™ Sheave directly on shaft)

The main consideration for a sheave without bearings is Pressure Velocity (PV). In this case, the Redco™ Sheave is the bearing. To calculate the load capacity for this situation, use the maximum PV value of the grade of Redco™ Cast Nylon to be used.

From here, calculate the MAXIMUM BORE PRESSURE by:

PB = PV/V

PB = Maximum Bore Pressure (psi)

PV = Pressure Velocity rating for the grade to be used (psi·fpm)
V = Surface speed of the bore of the sheave on the shaft (fpm)

For a Redco™ MD sheave, the bore pressure should not exceed 1,000 psi. With this, the MAXIMUM LOAD can be calculated.

 $Lmax = 1000 \cdot S \cdot LTB$ 

Lmax = Maximum Load (lbs)
S = Shaft Diameter (in.)
LTB = Length through bore (in.)

- LIGHT WEIGHT
- LONGER ROPE LIFE
- INCREASED LOADS
- DECREASED OPERATING COSTS
- CORROSION RESISTANT



#### **CUSTOM DESIGN & FABRICATION AVAILABLE**

Please refer to our website for a full list of services as well as physical properties and material specifications.

For more information on Redco™ products please call: CDN 1 800 667 0999 USA 1 866 733 2684

sales@redwoodplastics.com www.redwoodplastics.com







We cannot anticipate all conditions under which this information and our products or the products of other manufacturers in combination with our products may be used. We accept no responsibility for results obtained by the application of this or the safety and suitability of our products, whether alone or in combination with other products. Users are advised to make their own test to determine the safety and suitability of each such product or product combination for their own purposes. Unless otherwise agreed in writing, we sell the products without warranty, and buyers and users assume all responsibility and liability for loss or damage arising from the handling and use of our products, whether used alone or in combination with other products. For most recent technical information, phone 360 225 1491 in USA or 604 607 6000 in Canada.